

# 135

## Non-Activated Rosin Liquid Flux

### Product Description

Kester 135 non-activated rosin flux is an amber colored homogeneous solution rosin dissolved in a suitable solvent. The particular solvents used are liquids which exhibit the same non-corrosive and non-conductive properties as rosin itself. Kester 135 is carefully processed to remove foreign particles found in natural rosin. Under the older MIL-F-14256, this flux was QPL approved as Type R. Kester 135 is considerably more mobile because of its solids content and the low surface tension of the alcohol solvent. The high purity grade of alcohol solvent makes this flux very reliable for solderability testing.

#### Performance Characteristics:

- High quality for solderability testing
- Classified as ROL0 per J-STD-004

### Physical Properties

**Specific Gravity:** 0.880 ± 0.005

Antoine Paar DMA 35 @ 25°C

**Percent Solids (typical):** 40

Tested to J-STD-004, IPC-TM-650, Method 2.3.34

**Flash Point:** 18°C (64°F)

### Reliability Properties

**Copper Mirror Corrosion:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.3.32

**Corrosion Test:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.6.15

**Silver Chromate:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.33

**Chloride and Bromides:** None Detected

Tested to J-STD-004, IPC-TM-650, Method 2.3.35

**Fluorides by Spot Test:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.35.1

## Application Notes

### Flux Application:

Kester 135 is typically applied by a dip process.

### Process Considerations:

Kester non-activated rosin fluxes are used for applications where active flux is not permitted and critical electronic assemblies are involved. They are highly recommended for solderability testing of leads, printed circuit boards and other electrical components because of their consistently high quality.

### Flux Control:

Specific gravity is normally the most reliable method to control the flux concentration of rosin-based fluxes. To check concentration, a hydrometer should be used. The complex nature of the solvent system for the flux makes it imperative that Kester 4662 Thinner be used to replace evaporative losses. When excessive debris from circuit boards, such as board fibers and from the air line build up in the flux tank, these particulates will redeposit on the circuit boards which may create a build up of residues on probe test pins. It is, therefore, necessary to clean the tank and then replenish it with fresh flux when excessive debris accumulates in the flux tank.

### Cleaning:

Kester 135 flux residues are non-conductive, non-corrosive and do not require removal in most applications. If residue removal is required, call Kester Technical Support.

### Storage and Shelf Life:

Kester 135 is flammable. Store away from sources of ignition. Shelf life is 2 years from date of manufacture when handled properly and held at 10-25°C (50-77°F).

### Health & Safety:

This product, during handling or use, may be hazardous to health or the environment. Read the Material Safety Data Sheet and warning label before using this product.

---

**World Headquarters:** 800 West Thorndale Avenue, Itasca, Illinois, 60143 USA

**Phone:** (+1) 630-616-4000 • **Email:** customerservice@kester.com • **Website:** www.kester.com

#### Asia Pacific Headquarters

500 Chai Chee Lane  
Singapore 469024  
(+65) 6449-1133  
customerservice@kester.com.sg

#### European Headquarters

Zum Plom 5  
08541 Neuensalz  
Germany  
(+49) 3741 4233-0  
customerservice@kester-eu.com

#### Japanese Headquarters

20-11 Yokokawa 2-Chome  
Sumida-Ku  
Tokyo 130-0003 Japan  
(+81) 3-3624-5351  
jpsales@kester.com.sg

---