

CHEMTRONICS®

Technical Data Sheet

TDS # S200

CircuitWorks® Lead-Free Pocket Solder

PRODUCT DESCRIPTION

CircuitWorks® Lead-Free Pocket Solder is the high-purity pocket-sized solder in a convenient dispenser for rework and repair. This rosin core solder wire is manufactured from the lead-free solder alloy SAC 305. Lead-Free Pocket Solder is easy to use and produces reliable solder joints every time. Its activated pure rosin flux core eliminates troublesome solder voids. Instant wetting action provides thorough deoxidation of metallic surfaces providing the best possible surfaces for soldering.

- Simple to use, easy to carry
- Safe and environmentally friendly
- Precision manufactured SAC 305 solder
- Type RMA (rosin moderately activated) flux core
- Ensures reliable solder connections
- Cleans and wets heavily tarnished copper surfaces
- RoHS compliant

TYPICAL APPLICATIONS

CircuitWorks® Lead-Free Pocket Solder can be used for electronics applications in:

- Circuit Board Manufacturing, Rework and Repair
- Data Communications
- Instrumentation
- Controls
- General Maintenance and Repair

TYPICAL PRODUCT DATA AND PHYSICAL PROPERTIES

Solder Wire Diameter	0.040 in. (1 mm)
Flux Core	3%
Solder Composition	Tin (Sn) 96.5%
	Silver (Ag) 3.0 %
	Copper (Cu) 0.5%
Color	Silvery Metallic
Melting Point	419°-424°F (215°-219°C)

Flux Type Type ROM1
RoHS/WEEE
Status



CHEMICAL RESISTANCE

CircuitWorks® Lead-Free Pocket Solder has excellent resistance to all cleaners and aggressive organic solvents. Flux residues remaining after soldering can be easily cleaned with Chemtronics Flux-Off® Lead-Free Flux Remover (ES897B or ES1697) or CircuitWorks® Lead-Free Flux Remover Pen (CW9400).

COMPATIBILITY

The CircuitWorks® Lead-Free Pocket Solder material is generally compatible with materials used in printed circuit board fabrication. As with any material, compatibility with substrate should be determined on a non-critical area prior to use.

USAGE INSTRUCTIONS

Read MSDS carefully prior to use.

Application: Thread the solder wire through the hole in the dispenser. Solder can be used with hot soldering iron (600°F - 750°F) for normal soldering applications.

Cleaning: Flux residues remaining after soldering can be easily cleaned with Chemtronics Flux-Off® Lead-Free Flux Remover (ES897B or ES1697) or CircuitWorks® Lead-Free Flux Remover Pen (CW9400). Wipe residues from the board with a ControlWipe™ dry wipe.

AVAILABILITY

S200-72 1.0 mm (0.04") Diameter
 3.18 m (125") Length

TECHNICAL & APPLICATION ASSISTANCE

Chemtronics® provides a technical hot line to answer your technical and application related questions. The toll free number is: **1-800-TECH-401**.

NOTE:

This information is believed to be accurate. It is intended for professional end users having the skills to evaluate and use the data properly. ITW CHEMTRONICS® does not guarantee the accuracy of the data and assumes no liability in connection with damages incurred while using it.

MANUFACTURED BY:

ITW CHEMTRONICS®
8125 COBB CENTER DRIVE
KENNESAW, GA 30152

1-770-424-4888

REV. B (06/06)

Chemtronics®, CircuitWorks® and Flux-Off® are registered trademarks of ITW Chemtronics. All rights reserved.
ControlWipe™ is a trademark of ITW Chemtronics. All rights reserved.

DISTRIBUTED BY:

All-Spec Industries

Wilmington, NC

Ph: 800-537-0351

Fx: 800-379-9903

Email: sales@all-spec.com

Web: www.all-spec.com