

RT250 GFCI RECEPTACLE TESTER WITH LCD

For use with North American
3-wire 120V Electrical Outlets

Easy-to-read LCD
display shows

- Voltage
- Wiring-faults
- GFCI Trip Time



Featuring patent pending
detection of Open Neutral
Open Ground wiring fault



CAT II
135V

**KLEIN
TOOLS**



RT250 GFCI RECEPTACLE TESTER WITH LCD

The RT250 is an electrical receptacle tester that tests the wiring conditions at an electrical outlet and inspects GFCI devices. The LCD displays the voltage, identifies the wiring fault, and the time required to trip a GFCI device. It is designated for use with North American 3-wire 120V electrical outlets.

Test trip time of
ground fault circuit
interrupter

For use on 3-wire, North
American 120V electrical
outlets only

Auto-Hold is convenient
for hard-to-reach outlets.
Simply remove tester to
view the reading.

Large readout clearly
displays voltage and
GFCI trip time

**Large backlit
LCD display** shows
clear indication of
wiring conditions

GFCI button initiates a
ground fault. The
voltage and trip time
readings alternate in
the display.

**Bright green and
red LEDs** illuminate
for visual indicators

**Low battery
indicator.**
Tester comes with
2x AAA batteries;
compartment is
on back.

Power button; tester auto-powers
off after 3 minutes of inactivity to
conserve battery life.

WIRING CONDITIONS

- Wired Correctly
- Open Ground
- Open Neutral
- Open Hot
- Dual Open (Neutral & Ground)
Patent Pending
- Reversed Hot/Ground
- Reversed Hot/Neutral

CLEAR INDICATION OF VOLTAGE AND WIRING CONDITIONS



For Professionals
SINCE 1857™

Cat. No.	UPC	Description	Batteries Included	Height	Length	Width	Weight
RT250	69321-2	GFCI Receptacle Tester with LCD	2x AAA	1.1" (2.79 cm)	4.5" (11.4 cm)	2.0" (5.1 cm)	4.8 oz (136 g)

Warning statement: Visit www.kleintools.com for safety warnings.



See our complete line of **Test & Measurement Products**
www.kleintools.com



© 2020 Klein Tools, Inc.
Lincolnshire, IL 60069
82920 Rev. 04/20 A