

# E-SERIES ELECTRIC SCREWDRIVERS

- Various models that range from 0.9 - 21.7 lbf.in.
- Plugs directly into a power outlet. Does not require a separate power supply.
- Automatic power shut off once torque is achieved.
- Crafted to rest comfortably in the operators hand and reduces work fatigue with ergonomic handgrip.
- External torque adjustment scale.
- Push-to-Start and Lever Models available.
- Power cord with a noise filter to reduce electronic noise (EMC).
- Lightweight.



### Torque Ranges

Models	Driver Type	110V Item #	220V Item #	lbf.in	cN.m	RPM	Grip Dia	Drive Size
E180-A	Lever Start	145645	145646	0.9 - 15.6	10 - 176	1000	1 1/2"	1/4" F/Hex
E180-PS	Push-to-Start	145647	----	2.2 - 15.6	25 - 176	1000	1 1/2"	1/4" F/Hex
E250-A	Lever Start	145649	145650	1.3 - 21.7	15 - 245	630	1 1/2"	1/4" F/Hex
E250-PS	Push-to-Start	145651	----	2.2 - 21.7	25 - 245	630	1 1/2"	1/4" F/Hex

### Related Products

#### Torque Covers

Protects from incidental or operator tampering of torque setting.



**Color: Black**  
**Item # 145654**  
 For: E-Series



**Color: Blue**  
**Item # 145655**  
 For: E-Series



**Color: Green**  
**Item # 145656**  
 For: E-Series



**Color: Gold**  
**Item # 145657**  
 For: E-Series



**Color: Grey**  
**Item # 145658**  
 For: E-Series